

# ELECTRONICS UPGRADE WITH MATKO DISPLAY

TO CONVERT IDS-430 TO COMMUNICATE WITH MATKO  
DISPLAY AFTER REMOVING SCALE TECHNOLOGY  
DISPLAY YOU MUST RECONFIGURE CFG 89 & 90..

ENTER CFG MODE BY PRESSING AND HOLDING THE  
CLEAR KEY, THEN PRESS THE ENTER KEY.  
KEY IN 89 AND PRESS ENTER. ONCE IN CFG 89 YOU  
MUST KEY IN THE FOLLOWING CHANGES PRESSING  
ENTER AFTER EACH CHANGE...

C0-2, C01-254, C02-3, C03-82, C04-13, C05-10, C06-0, C07-71, C08-32, C09-13, C10-10, C11-0,  
C12-0

AFTER KEYING IN C12 TO 0, PRESS ENTER, THEN PRESS  
CLEAR ...

KEY IN 90 AND PRESS ENTER. ONCE IN CFG 90 YOU  
MUST KEY IN THE FOLLOWING CHANGES PRESSING  
ENTER AFTER EACH CHANGE...

C0-2, C01-254, C02-3, C03-71, C04-13, C05-10, C06-0, C07-71, C08-32, C09-13, C10-10, C11-0,  
C12-0

AFTER KEYING IN C12 TO 0, PRESS ENTER, THEN PRESS  
CLEAR AND THEN PRESS CLEAR AGAIN TO STORE..